

TYPICAL DETAIL
CONCRETE BASE, CONTROLLER CABINET

FILE NAME = USER NAME = wingram DESIGNED - REVISED PtNP-87-1608-12\Client\TSC Plans\Concrete Foundation, Type 1 Detail (For Cabinet, Model 30RANN - REVISED PLOT SCALE = %SCALE% CHECKED - REVISED PLOT DATE = 3/18/2010 DATE - REVISED -

STATE OF ILLINOIS DEPARTMENT OF TRANSPORTATION

FIBER OPTIC CABLE INSTALLATION - I-55 (LORENZO ROAD TO I-80) CONCRETE FOUNDATION, TYPE 1 DETAIL (FOR CABINET, MODEL 334)

F.A. RTE.		SEC.	TION			COUNTY	TOTAL SHEETS	SHEET NO.
55		2009-	-112 I			WILL	56	49
						CONTRACT NO. 60J24		
FED. RO	DAD DIST.	NO.	ILLINOIS	FED.	AID	PROJECT		

1. INSTALL FOUR ¾ INCH DIAMETER X 12 INCH MINIMUM LENGTH APPROVED J-BOLTS TO ANCHOR THE CABINET BASES. THE ANCHOR BOLTS SHALL BE CALVANIZED STEEL AND LOCATED AS DIRECTED BY THE ENGINEER TO

PROPERLY ANCHOR THE CONTROL CABINET TO THE BASE.

NOTES

- CONTROL CABINET BASE TOP SURFACES SHALL BE TROWEL FINISHED AND LEVEL, PRIOR TO CABINET INSTALLATION. LEVELING OF TOP SURFACES AFTER CONCRETE BASE HAS CURED SHALL ONLY BE ACCOMPLISHED BY GRINDING.
- 3. MAINTENANCE PLATFORMS ARE NOT REQUIRED WHEN THE SURROUNDING AREA IS PAYED.
- 4. CONCRETE FORM DEPTH BELOW FINISHED GRADE SHALL BE 6" MAXIMUM, CONCRETE FORMS SHALL BE REMOVED AFTER CONCRETE HAS SET.
- 5. CONCRETE MAINTENANCE PLATFORM AND CABINET FOUNDATION FOR CABINET SHALL BE A MONOLITHIC POLIC.
- WHEN REQUIRED TO CONNECT NONMETALLIC CONDUIT TO METALLIC CONDUIT, ONLY ADAPTER FITTINGS, U.L. LISTED FOR ELECTRICAL USE, SHALL BE USED.
- 7. CONDUIT HEIGHT ABOVE THE CONCRETE BASE SHALL BE 3 INCH.
- 8. MINIMUM BENDING RADIUS OF CONDUIT = 6 X THE DIAMETER.
- 9. ALL METALLIC CONDUIT ENDS SHALL BE REAMED AND THREADED.
- 10. CAP ALL BELOW GRADE METALLIC CONDUIT ENDS IN WHICH WIRE OR CABLE IS NOT BEING INSTALLED.
- 11. PLUG ALL BELOW GRADE NONMETALLIC CONDUIT ENDS IN WHICH WIRE OR CABLE IS NOT BEING INSTALLED.
- 12. ALL CONDUIT ENDS AT THE TOP OF CONCRETE BASES SHALL BE CAPPED IF METALLIC OR PLUGGED IF NONMETALLIC IMMEDIATELY AFTER PLACEMENT AND BEFORE CONCRETE IS POURED. CONDUITS IN WHICH WIRE OR CABLE IS NOT BEING INSTALLED SHALL REMAIN CAPPED OR PLUIGGED.
- 13. ALL METALLIC CONDUIT ENDS AT TOP OF CONCRETE BASES SHALL HAVE BUSHINGS AND ALL NON METALLIC CONDUIT ENDS AT TOP OF CONCRETE BASES SHALL HAVE END BELLS.